


**Test instrument**
[中文版](#)
[HOME](#)
[ABOUT V&A](#)
[TRADE SHOW](#)
[SERVICE](#)
[CONTACT US](#)
[SITE MAP](#)

## Environmental instrument

**Products**
[CALIBRATOR  
AND INS  
MULTIMETER](#)
[EXTRA-  
SAFETY  
MULTIMETER](#)
[BENCH  
MULTIMETER](#)
[DMM AND  
CLAMP METER](#)
[ENVIRONMENTAL  
INSTRUMENT](#)
[INFRARED  
THERMOMETER](#)
[LCR  
METER](#)
[OTHER TEST POWER  
INSTRUMENT SUPPLY](#)
[ACCESSORY](#)
**ENVIRONMENTAL  
INSTRUMENT**

· VA8010
· VA8020 series
· VA8030
· VA8090
· VA8050/VA8051
· VA8060
· VA8070
· VA8080 >
· VA8040
· VA8041

### VA8080 Sound level meter



#### VA8080 Sound level meter

The Sound Level Meter has been designed to measure sound level for various environments. It is used to detect noise, music level or sound engineering...

#### SPECIFICATIONS:

- Standard applied: IEC651 Type2, ANSI S1.4 Type 2
- Frequency range: 31.5Hz~8KHz
- Measuring range: 30—60dB, 50—80dB, 70—100dB, 90—120dB
- Frequency weighting: A Type
- Digital display: 4 digitals
- Resolution: 0.1 dB.
- Accuracy: 30~60dB  $\pm 3$  dB; 60~120dB  $\pm 2$  dB
- Time response: Analog bar: 125ms ; Digital :750ms
- Operating temperature: 0~+40°C
- Operating humidity: 10 ~ 80%RH

#### FEATURES:

- automatic ranging / manual ranging selection.
- Analog bar indicator.
- Frequency weighting A Type.
- Range display.
- Automatic shutdown / continuous working mode selection.
- Low battery voltage indication.
- Sound OVER or UNDER display.
- Software calibrating to insure high reliability.
- Good circuit designed to save power.
- Small volume , large LCD.

- Low power consume
- Complete with pouch case
- Power supply: DC1.5V (AAA) x 3pcs

| [HOME](#) | [ABOUT V&A](#) | [PRODUCTS](#) | [NEW PRODUCTS](#) | [SERVICE](#) | [TRADE SHOW](#) | [CONTACT US](#) | [SITE MAP](#) |

Copyright 2005 SHANGHAI YIHUA V&A INSTRUMENT CO.,LTD. All Rights Reserved