



## DC POWER SUPPLY

### Products

CALIBRATOR

DIGITAL  
MULTIMETER

CLAMP  
METER

IR  
THERMOMETER

LCR METER

OTHER TEST  
INSTRUMENT

DC POWER  
SUPPLY

ACCESSORY

#### DC POWER SUPPLY

- Single output
- Double output
- Triple output >
- Others



#### DC Power supply

##### HY3002D-3 / HY3003D-3 / HY3005D-3

MODEM	HY3002D-3	HY3003D-3	HY3005D-3
Input Voltage	110/220V±10%AC		
Output Voltage	2×0~30V		
Output Current	2×0~2A	2×0~3A	2×0~5A
Source Effect	CV≤0.01%±1mV; CC≤0.02%±1mA		
Load Effect	CV≤0.01%±5mV; CC≤0.02%±5mA		
Ripple & Noise	≤1mVrms		
Fixed Output	5V/3A		
Display	Four 3 1/2 digit LCD display		
Accuracy	V: ±1%±2digits; C: ±2%±2digits		
Size	365×265×164mm		
Weight	8~12kg		



##### HY3002-3 / HY3003-3 / HY3005-3

MODEM	HY3002-3	HY3003-3	HY3005-3
Input Voltage	110/220V±10%AC		
Output Voltage	0~30V		
Output Current	2×0~2A	2×0~3A	2×0~5A
Source Effect	CV≤0.01%±1mV; CC≤0.02%±1mA		
Load Effect	CV≤0.01%±5mV; CC≤0.02%±5mA		
Ripple & Noise	≤1mVrms		
Fixed Output	5V/3A		
Display	Two 3 1/2 digit LED display		
Accuracy	V: ±1%±2digits; C: ±2%±2digits		
Size	365×265×164mm		
Weight	8~13kg		



##### HY3002S-3 / HY3003S-3 / HY3005S-3

MODEM	HY3002S-3	HY3003S-3	HY3005S-3
Input Voltage	110/220V±10%AC		
Output Voltage	0~30V		
Output Current	2×0~2A	2×0~3A	2×0~5A
Source Effect	CV≤0.01%±1mV; CC≤0.02%±1mA		
Load Effect	CV≤0.01%±5mV; CC≤0.02%±5mA		
Ripple & Noise	≤1mVrms		
Fixed Output	5V/3A		
Display	Two voltmeters & two amperometers display		
Accuracy	2.5%f.s.		
Size	365×265×164mm		
Weight	9~13kg		